LED Driver with Phasecut dimmer

DRIVER PHASECUT 36W/24V IP20 RADIUM

Radium

Product Datasheet Date: 11.11.2026



General Data

Artikel Nr.	OTDA3025
Bestellzeichen	DRIVER PHASECUT 36W/24V IP20 RADIUM
EAN-Faltschachtel	4003556009875
Versandeinheit in Stk.	60
EAN Umkarton (Versandeinheit)	4003556409873
Brutto-Gewicht Versandeinheit in kg	11.35
Länge Versandeinheit in m	0.37
Breite Versandeinheit in m	0.34
Höhe Versandeinheit in m	0.0165
Product weight	165 g
Produktstatus	Inaktiv

Electric Parameters

Rated value output power max.	36.0 W
Output power	0-36.0 W
Input voltage AC (range)	220-240 V
Output Voltage	24 V
Output voltage	23.5-24.5 V
Number of Channels	1
Inrush current	40 A
Input current max.	0.4 A
Output current	0-1500 mA
Mains frequency	50 / 60 Hz

LED Driver with Phasecut dimmer

DRIVER PHASECUT 36W/24V IP20 RADIUM

Radium

Electric Parameters

Suitable for DC-voltage (primary side)	Nein
dimmable	Ja
Dimming with push-button	Ja
Dimming interface	Phase-Cut, for Push-DIM* operation, please note*

Light Application Parameters

Dimming range	0 - 100 %

Service Life

Service life	30000 h
Tc Temperature max.	70 °C

Specification

Mean efficiency	87 %
Length	175 mm
Height max.	30 mm
Width	44 mm
Model	Dynamic

Notes on Operation

Degree of protection (IP)	IP20
Protection class	II
Ambient temperatures	-30…+55 °C
Tc Temperature max.	70 °C
max. relative air humidity	95 %

Miscellaneous

Similar products	OTDA3026, OTDA4078

Notes

1 channel constant voltage supply 24V

Please, refer to www.radium.de/recycling for notes on disposal of burned-out lamps as well as lamp breakage.
The "lifespan L70" described for LED lamps indicates the number of hours when the luminous flux has decreased to 70% of its initial value.
The optinal field 'info about service life' contains the frame conditions according to standards based on which the specific service life has been determined. So, for example, "12B50, 50Hz" means that the mean service life (B50) has been determined with a 12h switching cycle at mains (frequency 50Hz), "3B50, HF" is based on a 3h switching cycle at electronic control gear (high frequency).

LED Driver with Phasecut dimmer
DRIVER PHASECUT 36W/24V IP20 RADIUM

Radium

Besonderheiten



Allgemeine Hinweise

* If the light sources in Push-Dim operation can no longer be switched at the same time or dimmed evenly when operating the lighting system with SEVERAL drivers on ONE switch button, the system works asynchronously and can be synchronized again using a RESET routine:
1. Step: LONG press (> 0.5 s) => all lights switch ON
2. Step: SHORT press (< 0.5 s) => all lights switch OFF
3. Step: LONG press (> 0.5 s) => all lights switch ON and dim
[4. Step: Double click => save dimming setting (optional)]
The drivers then behave synchronously again.

The technical design data in accordance with DIN and IEC. The producer does not take any responsibility for damage to persons or property in case of unsuitable operation or handling of the product. Operating data and dimensions are valid within the usual tolerances. Related lamp types (different bases, mains voltages) may be available on request. Sale and delivery are effected in accordance with the Radium Terms of Delivery and Payment valid on the day of conclusion of contract. Packing units offer economical advantages to the purchase and logistic department. Please match your quantity volume accordingly. For orders of a minimum quantity (clefts) with a lamp model the amount lower than the volume of each packaging unit, we will invoice 10 % additional charge per lamp type. Technical changes and terms of delivery are reserved. Manipulation of any kind to packaging or product is not permissible as this will violate Radium brand rights. Furthermore, technical properties of the product can change to its disadvantage or even destruction. Therefore, Radium cannot be responsible for consequential damages.
® = Registered trademark
Subject to change without notice. Errors and omissions excepted.

All technical data without guarantee.