
Metal halide lamp with quartz burner
HRI-TS 2000W/D/400/E40

Radium

Product Datasheet Date: 11.11.2026





A+	180000	6000K	4 000h

General Data

Artikel Nr.	32416569
Bestellzeichen	HRI-TS 2000W/D/400/E40
EAN-Faltschachtel	4008597165696
Versandeinheit in Stk.	4
EAN Umkarton (Versandeinheit)	4008597465697
Brutto-Gewicht Versandeinheit in kg	3.115
Länge Versandeinheit in m	0.64
Breite Versandeinheit in m	0.27
Höhe Versandeinheit in m	0.29
Product weight	484 g
Produktstatus	Aktiv

Electric Parameters

Wattage	2000.0 W
Lamp nominal wattage	2 kW
Mains voltage	400 V
Ignition voltage	4.0 up to 5.0
Hot restrike voltage	60 kV

Metal halide lamp with quartz burner
HRI-TS 2000W/D/400/E40

Radium

Electric Parameters

Lamp's nominal current	10.2 A
Nominal choke current	10.3 A
Compensation capacitor for 50Hz operation	60 µF
Running up current max.	190%
Fuse	Daelay-action; min. double nominal current
dimmable	Nein
Controllable (in suitable circuit)	Nein

Light Application Parameters

Luminous flux	180000 lm
Rated lamp luminous flux	180000 lm
Efficacy / Luminous efficiency	90 lm/W
Total mains efficacy	83 lm/W
Light colour	daylight
Colour temperature	6000 K
Color rendering index	93
Rated colour rendering index Ra	83
Lumen maintenance at 2000h	0.88
Lumen maintenance at 4000h	0.83
Lumen maintenance at 6000h	0.78
Lumen maintenance at 8000h	0.75
Lumen maintenance at 12000h	0.70
Lumen maintenance at 16000h	0.65

Service Life

Average life	4000 h
Lamp survival factor at 2000h	0.97
Lamp survival factor at 4000h	0.50
Lamp survival factor at 6000h	0.47

Specification

Energylabel notice	no Label needed (> 82.000 lm)
Energylabel (E -> A++)	A+
Diameter	100 mm
Length	495 mm
Total length max.	495 mm

Metal halide lamp with quartz burner
HRI-TS 2000W/D/400/E40

Radium

Specification

Burning position	p30
Mercury content	180.0 mg
Lamp shape	Tube, double-ended
Model	Clear
Base	E40
Colour	White

Notes on Operation

Burning position	p30

Information especially for EPREL

Energylabel notice	no Label needed (> 82.000 lm)

Miscellaneous

EU Directive	TIM

Notes

MH lamp with quartz burner, tubular bulb clear, daylight, base E40. Operation in enclosed luminaire, with ballast and (hot restrike-)ignitor.

Please, refer to www.radium.de/recycling for notes on disposal of burned-out lamps as well as lamp breakage.
The "lifespan L70" described for LED lamps indicates the number of hours when the luminous flux has decreased to 70% of its initial value.
The optinal field 'info about service life' contains the frame conditions according to standards based on which the specific service life has been determined. So, for example, "12B50, 50Hz" means that the mean service life (B50) has been determined with a 12h switching cycle at mains (frequency 50Hz), "3B50, HF" is based on a 3h switching cycle at electronic control gear (high frequency).


Sockelübersicht




E40
IEC/EN 60061-1
sheet 7004-24-6

Spektrale Strahlungsverteilung
Natural daylight is a mixture of direct sunlight and the light of the sky. Therefore, its spectral composition changes permanently due to the changing time of day. The standardised light classification D65 corresponds to a daylight with a colour temperature of approximately 6500 K.
Every discharge lamp type has got an individual spectral power distribution according to its chemical filling. From this result important properties light colour or colour rendering.
Should the spectral lines be very close together the lamp presumably has got a very good colour rendering index, so, Ra might be near 100. Does the spectrum rather look like single lines or frayed out the colour rendering of the lamp will probably be not as good.
If number and height of the spectral lines within the blue range (around 400 nm) prevails it might be a lamp with a rather cold light colour like for example daylight. On the other hand, should the red (around 700 nm) or the red and yellow (around 600 nm) range be dominant one can assume that the lamp will be a rather warm light colour like WDL.
After the lamp start a metal hlide lamp needs about 2-4 minutes time to reach its full luminous flux, all colours in the spectrum are within the discharge arc then.
Visible region from 380 to 780 nm; height of graph corresponding with relative spectral emission (400mW/klm) per 10nm.

Metal halide lamp with quartz burner
HRI-TS 2000W/D/400/E40




HRI.../D




daylight(D 65)

Schaltbeispiel(e)



Standard circuit HID with external ignitor
Key:
L. = lamp
VG = electromagnetic ballast (KVG/VVG)
P = phase
N = zero potential
K = p. f. correction capacitor
Z = ignitor


The required control gear (here ignitor and ballast) for the lamps operation is usually mounted in the suitable luminaire in an appropriate electric circuit. Changes of any kind are to be conducted by qualified and specialised staff, only. Thus, this circuit example is to be understood merely as a technical background information for interested users.



Circuit for 400V-HID-lamps suitable for hot restrike
Key:
L. = lamp
VG = electromagnetic ballast (KVG/VVG)
P = phase
N = zero potential
K = p. f. correction capacitor
Z = ignitor

S = fuse


The required control gear (here fuse, capacitor, ignitor and ballast) for the lamps operation is usually mounted in the suitable luminaire in an appropriate electric circuit. Changes of any kind are to be conducted by qualified and specialised staff, only. Thus, this circuit example is to be understood merely as a technical background information for interested users.



Circuit for 400V-HID-lamps suitable for hot restrike
Key:
L. = lamp
VG = electromagnetic ballast (KVG/VVG)
P = phase
N = zero potential
K = p. f. correction capacitor
Z = ignitor

S = fuse

The required control gear (here fuse, capacitor, ignitor and ballast) for the lamps operation is usually mounted in the suitable luminaire in an appropriate electric circuit. Changes of any kind are to be conducted by qualified and specialised staff, only. Thus, this circuit example is to be understood merely as a technical background information for interested users.



Circuit for 400V-HID-lamps suitable for hot restrike
Key:
L. = lamp
VG = electromagnetic ballast (KVG/VVG)
P = phase
N = zero potential
K = p. f. correction capacitor
Z = ignitor

S = fuse

Metal halide lamp with quartz burner
HRI-TS 2000W/D/400/E40

The required control gear (here fuse, capacitor, ignitor and ballast) for the lamps operation is usually mounted in the suitable luminaire in an appropriate electric circuit. Changes of any kind are to be conducted by qualified and specialised staff, only. Thus, this circuit example is to be understood merely as a technical background information for interested users.

Besonderheiten



Allgemeine Hinweise

The technical design data in accordance with DIN and IEC. The producer does not take any responsibility for damage to persons or property in case of unsuitable operation or handling of the product. Operating data and dimensions are valid within the usual tolerances. Related lamp types (different bases, mains voltages) may be available on request. Sale and delivery are effected in accordance with the Radium Terms of Delivery and Payment valid on the day of conclusion of contract. Packing units offer economical advantages to the purchase and logistic department. Please match your quantity volume accordingly. For orders of a minimum quantity (clefts) with a lamp model the amount lower than the volume of each packaging unit, we will invoice 10 % additional charge per lamp type. Technical changes and terms of delivery are reserved. Manipulation of any kind to packaging or product is not permissible as this will violate Radium brand rights. Furthermore, technical properties of the product can change to its disadvantage or even destruction. Therefore, Radium cannot be responsible for consequential damages.
® = Registered trademark
Subject to change without notice. Errors and omissions excepted.

All technical data without guarantee.